

**Kable Lite Surface Transformer-300W Mag**



**DESCRIPTION**

This single-feed surface transformer converts standard 120 volt line-voltage to 12 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 300 watts. The transformer is concealed inside a decorative housing with a fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.



**INSTALLATION**

This product can mount to either a 4" square electrical box with round plaster ring or an octagon electrical box (not included).

**OTHER**

The shortest rigid standoff that can be used with this surface transformer is the 5" rigid post standoff (sold separately). This surface transformer may be plugged in with the addition of a Plug Option, a 16' cord with plug (sold separately). 12 volt transformers require the use of 12 volt lamps.

**WEIGHT**

12.15lb / 5.51kg ±

**ORDERING INFORMATION**

**700SRT30D** FINISH

- Z ANTIQUE BRONZE
- B BLACK
- C CHROME
- S SATIN NICKEL
- W WHITE

As a general rule when using LED fixtures we do not recommend using greater than 70% of specified maximum wattage on the transformer due to inrush current. for assistance, please contact our technical support department.



700SRT30D _____
FIXTURE TYPE: _____
JOB NAME: _____
NOTES: _____
_____
_____