

F R E E J A C K



FreeJack 4" Square Flush Canopy LED LED T20

DESCRIPTION

4" Square Flush Canopy LED accommodates both LED and Halogen fixtures with a Freejack connector. Electronic transformer (included) fits in junction box. One FreeJack port; for ceiling or wall.

INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. One FreeJack port. Install on ceiling or wall. If wall mounting, head should be no longer than 6".



OTHER

For use with any 12 volt LED or Halogen FreeJack Pendant or head (50 watts max). Pendants and heads sold separately.

WEIGHT

0.8lb / 0.36kg ±



freejack 4" square
flush canopy led

ORDERING INFORMATION

700FJ4SQ SHAPE OR SIZE	FINISH	VOLTAGE
4" SQUARE INTEGRAL TRANSFORMER	Z ANTIQUE BRONZE C CHROME S SATIN NICKEL	-LED 120V IN/12V OUT LED - 277V IN/12V OUT LED LED277



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700FJ4SQ _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____

