

K A B L E L I T E

Kable Lite Remote Kit 300w

DESCRIPTION

Includes 45' of bare cable (enough for a twenty foot wall-to-wall run), two pairs of slimline turnbuckles, a power feed canopy and a 12 volt 300 watt remote magnetic transformer. Add up to six 50 watt elements or up to eight 35 or 37 watt elements.

INSTALLATION

Magnetic transformer installs in an accessible location behind the ceiling or wall. Canopy mounts to a standard 4" junction box with round plaster ring (provided by electrician) and includes 24" hardwire leads.



ORDERING INFORMATION

700KLKTA300 FINISH

- C CHROME
- S SATIN NICKEL



TECH LIGHTING®
7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700KLKTA300 _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2015 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.